




UPS SELECTOR GUIDE

3 SERIES STANDBY UPS - BACK UP POWER


3S	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Plugboard 	3S600AU	600/360	Aus 10 Amp	x4 surge x4 battery		USB		2 Years	
	3S850AU	850/510							


5 SERIES LINE-INTERACTIVE UPS - KEEPING IT SMOOTH

5E Gen 2	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Tower 	5E700UIAU	700/360	Aus 10 Fixed Input Lead	2 x		USB		2 Years	
	5E900UIAU	900/480		2 x					
	5E1200UIAU	1200/660		3 x					
	5E1600UIAU	1600/900		3 x					
	5E2200UIAU	2200/1200		3 x					

5S	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Tower 	5S550AU	550/330	Aus 10 Amp	3 x battery + surge 3 x surge only		USB		2 Years	
	5S700AU	700/420							
	5S850AU	850/510							
	5S1200AU	1200/750							
	5S1600AU	1600/1000							

5SC	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Tower 	5SC500i	500/350	IEC C14	4 x		USB/RS232 serial port and relay contacts		2 Years	
	5SC750i	750/525		6 x					
	5SC1000i	1000/700		8 x					
	5SC1500i	1500/1050		8 x					

5SC	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Rack 	5SC1500IR-AU	1500/1050	IEC C14	8 x		USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS	P0UBHV10IU	2 Years	

5SX	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Rack / Tower 	5SX1250AU	1250/1125	IEC C14	8 x	5SXEBM48R2U (can have maximum of 4)	USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS	P0UBHV10IU	2 Years	
	5SX1750AU	1750/1575		8 x	5SXEBM48R2U (max 4)				
	5SX3000AU	3000/2700		6 x 1 x	5SXEBM72R2U (max 4)				
	5SX3000AU	3000/2700		6 x 1 x	5SXEBM72R2U (max 4)				
	5SX3000AU	3000/2700		6 x 1 x	5SXEBM72R2U (max 4)				
	5XKRACKKIT2U	If Rackmounting add							

5P Gen 2	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Rack 	5P650IRG2	650/420	IEC C14	4 x		USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS	P0UBHV10IU	3 Years	
	5P850IRG2	850/600		4 x					
	5P1150IRG2	1150/770		6 x					
	5P1550IRG2	1550/1100		6 x					


5P Gen 2	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Tower 	5P650AU62	650/420	IEC C14	4 x		USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS		3 Years	
	5P850AU62	850/600		6 x					
	5P1150AU62	1150/770		8 x					
	5P1550AU62	1550/1100		8 x					


APPLICATIONS

- CCTV
- Switch board & controls
- Motors
- Emergency lighting
- Communications
- Desktops
- Point of sale
- Storage
- Servers
- Home


INPUT / OUTLET

- Aus 10 Amp
- IEC C13/14
- IEC C19/20

5P Lithium Ion	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Rack 	5P1550GR-L	1550/1100	IEC C14	6 x		USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS	P0UBHV10IU	5 Years	


5PX Gen 2	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Rack / Tower 	5PX1500IRT2UAUG2	1500	IEC C14	8 x	5PXEBM48RT (max 4)	USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS	P0UBHV10IU	3 years	
	5PX2000IRT2UAUG2	2000			5PXEBM48RT (max 4)		P0UBHV10IU		
	5PX2200IRT2UAUG2	2200			5PXEBM72RT3U (max 4)		MBP3KI		
	5PX3000IRT2UAUG2	3000			5PXEBM72RT3U (max 4)		MBP3KI		
	5PX3000IRT3UAUG2	3000			5PXEBM72RT3U (max 4)		MBP3KI		


9 SERIES ONLINE UPS - TOTAL PROTECTION

9E	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Tower 	9E1000IAU	1000/800	IEC C14	4 x	NA	USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS	P0UBHV10IU	1 year	
	9E2000IAU	2000/1600		6 x	9EEBM72 (max 4)		P0UBHV10IU		
	9E3000IAU	3000/2400		6 x	9EEBM72 (max 4)		MBP3KI		
	9E6KI	6000/4800		Hard Wired	Terminal block		9EEBM180 (max 4)		

9SX	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Tower 	9SX700-AU	700/630	IEC C14	4 x	NA	USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS	P0UBHV10IU	2 years	
	9SX1000-AU	1000/900		4 x	9SXEBM36T (max 4)		P0UBHV10IU		
	9SX1500-AU	1500/1350		4 x	9SXEBM48T (max 4)		P0UBHV10IU		
	9SX2000-AU	2000/1800		5 x 1 x	9SXEBM96T (max 4)		P0UBHV10IU		
	9SX3000-AU	3000/2700		5 x 1 x	9SXEBM96T (max 4)		MBP3KI		
	9SX6KI-AU	6000/5400		Hard Wired	Ph = N = E Terminal block		9SXEBM240T (max 4)		

9PX 1-3KVA	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Rack / Tower 	9PX1000IRT2U	1000	IEC C14	8 x	9PXEBM48RT2U (max 4)	USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS Output Relay	P0UBHV10IU	3 Years	
	9PX1500IRT2U	1500		8 x	9PXEBM48RT2U (max 4)		P0UBHV10IU		
	9PX2000IRT2U	2000/1800		4 x 2 x	9PXEBM72RT2U (max 4)		MBP3KI		
	9PX2200IRT2U	2200		8 x 2 x	9PXEBM72RT2U (max 4)		MBP3KI		
	9PX2200IRT3U	2200		8 x 2 x	9PXEBM72RT3U (max 4)		MBP3KI		
	9PX3000IRT2U	3000		8 x 2 x	9PXEBM72RT2U (max 4)		MBP3KI		
	9PX3000IRT3U	3000		8 x 2 x	9PXEBM72RT3U (max 4)		MBP3KI		

9PX 5-11KVA	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Rack/Tower 	9PX5KI	5000/4500	Hard Wired	HW, 2 x 8 x	9PXEBM180 (max 4)	USB/RS232 and 1 communication slot for either Network-M3 or RELAY-MS DB9 (4) Dry Contacts/ DB15 Parallel	MBP6KI	3 Years	
	9PX6KI	6000/5400		HW, 2 x 8 x	9PXEBM180 (max 4)		MBP6KI		
	9PX8KIPM + 9PXEBM240	8000/7200		HW, 4 x	9PXEBM240 (max 4 or 12 with supercharger SC240RT module)		MBPTIKI		
	9PX11KIPM + 9PXEBM240	11000/10000		HW, 4 x	9PXEBM240 (max 4 or 12 with supercharger SC240RT module)		MBPTIKI		

9PX Lithium Ion	Part Number	VA/Watts	Input	Outlet	EBM	Comms	Bypass Switch	Warranty	Applications
Rack 	9PX1500IRTANZ-L	1500/1500	IEC C14	8 x	9PXEBM48RTIU-L (max 4)	USB/RS232, mini-terminal block and 1 communication slot for either Network-M3 or RELAY-MS	P0UBHV10IU	5 Years	
	9PX2000IRTAL-L	2000/1800		6 x 2 x	9PXEBM72RTIU-L (max 4)		MBP3KI		
	9PX3000IRTANZ-L	3000/2400		8 x 2 x	9PXEBM72RTIU-L (max 4)		MBP3KI		
	9PX6KIRTN-L	6000/5400		Hard wired	Terminal Block		9PXEBM192RT2U-L (max 4)		